

TUNGSTEN HALOGEN LAMPS • SINGLE ENDED QUARTZ

- Miniature Bi-Pin & Glass 2-Pin Base
- Compact C-6 Filament \*
- Operate in any position

hi-Tech lamps

800-229-6509

info@hi-techlamps.com



| Watts                             | Ushio Ordering Code | Ushio Lamp Code | Volts | Dimensions |         |         | Filament Type | Approx Lumens lm | Color Temp K | Avg Life h |
|-----------------------------------|---------------------|-----------------|-------|------------|---------|---------|---------------|------------------|--------------|------------|
|                                   |                     |                 |       | Dia (A)    | OAL (B) | LCL (C) |               |                  |              |            |
| <b>Miniature Bi-Pin Base - G4</b> |                     |                 |       |            |         |         |               |                  |              |            |
| 2.4                               | 1000863             | JC6V-2.4W       | 6     | 9          | 28      | 19.5    | C-6           | 35               | 2934         | 100        |
| 3                                 | 1000854             | JC4V-3W         | 4     | 9          | 28      | 19.5    | C-6           | 35               | 2868         | 800        |
| 3                                 | 1000870             | JC6V-3W         | 6     | 9          | 28      | 19.5    | C-6           | 46               | 3036         | 100        |
| 5                                 | 1000874             | JC6V-5W         | 6     | 9          | 28      | 19.5    | C-6           | 100              | 3006         | 50         |
| 5                                 | 1000833             | JC12V-5W        | 12    | 9          | 28      | 19.5    | C-6           | 60               | 2720         | 2000       |
| 6                                 | 1000876             | JC6V-6W         | 6     | 9          | 28      | 19.5    | C-6           | 100              | 3085         | 100        |
| 6                                 | 1000884             | JC9V-6W         | 9     | 9          | 28      | 19.5    | C-6           | 100              | 2998         | 50         |
| 8                                 | 1000878             | JC6V-8W         | 6     | 9          | 28      | 19.5    | C-6           | 163              | 3168         | 50         |
| 10                                | 1000856             | JC6V-10W        | 6     | 9          | 30      | 19.5    | C-6           | 130              | 2850         | 2000       |
| 10                                | 1000882             | JC9V-10W        | 9     | 9          | 28      | 19.5    | C-6           | 230              | 3078         | 50         |
| 10                                | 1000812             | JC12V-10W       | 12    | 9          | 28      | 19.5    | C-6           | 175              | 2916         | 300        |
| 12                                | 1000859             | JC6V-12W        | 6     | 9          | 28      | 19.5    | C-6           | 238              | 3180         | 50         |
| 12                                | 1000815             | JC12V-12W       | 12    | 9          | 28      | 19.5    | C-6           | 276              | 3100         | 50         |
| 15                                | 1000861             | JC6V-15W        | 6     | 9          | 28      | 19.5    | C-6           | 300              | 3138         | 100        |
| 20                                | 1000866             | JC6V-20W        | 6     | 9          | 30      | 19.5    | C-6           | 280              | 2850         | 2000       |
| 20                                | 1000821             | JC12V-20W       | 12    | 9          | 30      | 19.5    | C-6           | 350              | 2850         | 2000       |
| 20                                | 1000844             | JC24V-20W       | 24    | 9          | 30      | 19.5    | C-6           | 280              | 2850         | 2000       |
| 35                                | 1000825             | JC12V-35WB      | 12    | 9          | 30      | 19.5    | C-6           | 650              | 2900         | 2000       |
| <b>Glass 2-Pin Base - G6.35</b>   |                     |                 |       |            |         |         |               |                  |              |            |
| 20                                | 1000822             | JC12V-20W       | 12    | 11         | 44      | 30.0    | C-6           | 280              | 2850         | 2000       |
| 35                                | 1000823             | JC12V-35W       | 12    | 11         | 44      | 30.0    | C-6           | 650              | 2900         | 2000       |
| <b>Glass 2-Pin Base - GY6.35</b>  |                     |                 |       |            |         |         |               |                  |              |            |
| 50                                | 1000827             | JC12V-50W       | 12    | 11         | 44      | 30.0    | C-6           | 1000             | 3000         | 2000       |
| 75                                | 1000835             | JC12V-75W       | 12    | 11         | 44      | 30.0    | C-6           | 1600             | 3000         | 2000       |
| 100                               | 1000806             | JC12V-100WG     | 12    | 11         | 44      | 30.0    | C-6           | 2300             | 3000         | 2000       |

Originally developed as light sources for optical instruments, JC lamps feature an overall compact design with precise LCL placement. The exceptional brightness of this compact lamp make this series an ideal choice for task light applications.

\* Also available with C-8 Filament

